


# CSD210/211/212 CSD230/231/232





for direct or indirect current monitoring in 3-phase AC, 3-phase N/AC or up to 3 AC circuits





- electronic measuring relay
- high reliability and galvanically separation by built-in current transformer
- impulse-voltage proof and HF-noise resistant in accordance with VDE and IEC
- built-in alarm LEDs
- stepless adjustable range
- stepless adjustable response time
- connection terminals for easy assembly
- three respectively one separated measuring inputs
- three respectively one alarm relay


# **Product description**


The response values marked on the setting scale are adjusted for current rise (use as overcurrent relay). If one or several input currents exceed the response setting Y, the output relay receives a switching signal after the selected delay period has expired, and the corresponding LED indicates I>Y. The selectable response delay is effective only with current rise. With current drop the unit will switch within approx. 0.1 - 0.2 seconds.

The output relay function can be selected (N/C or N/O operation).

#### Note:

With relay types CSD230/CSD231/CSD232 the time delay is effective only for the first overcurrent signal. Once the first signal has arrived, subsequent signals coming from the remaining measuring circuits are output without delay.






### Legend

switching hysteresis Ну K1... output relay built-in alarm LED IFD

current

auxiliary voltage UH adjusted response value Υ... adjusted response delay



#### **Technical Data**

Insulation coordination acc. to IEC 60	664-1:
Rated insulation voltage	AC 250 V
Rated impulse withstand voltage/contamination	ation level 4 kV/3
Dielectric test acc. to IEC 60255	2.5 kV
Supply voltage	
Supply voltage U	AC 4070 Hz 240/220/127/110/100/42/24 V
Voltage range of U	0.8 1.15 x U <sub>น</sub>
Max. power consumption	4.5 VÄ
Response values	
Response value (steplessly adjustable)	
CSD210/CSD230	0.1 1A
CSD211/CSD231	0.5 5 A
CSD212/CSD232	1 10 A

nespones raids (eropisses) adjustable)	
CSD210/CSD230	0.1 1A
CSD211/CSD231	0.5 5 A
CSD212/CSD232	1 10 A
Influence of ambient temperature	< 0.05 % / °C
Influence of frequency	< 0.1 % / Hz
Switching hysteresis	ca. 3 %
Response delay (steplessly adjustable)	0.1 10 sec.
Ready to trip time (max.)	0.2 sec.
OFF-delay	approx. 0.1 0.2 sec.
Influence of ambient temperature	< 0.2 % / °C

initiating of anibion temperature	1 0.E 707 0	
Contact circuit		
Switching components	see wiring diagram	
Contact class acc. to DIN IEC 60255 Teil 0-20	IIB	
Rated contact voltage	AC 250 V/DC 300 V	
Admissible number of operations	12000 cycles	
Limited making capacity	UC 5 A	
Limited breaking capacity		
at AC 230 V and cos phi = 0.4	AC 2 A	
at DC 220 V and $L/R = 0.04 s$	DC 0.2 A	
Operating principle	N/C- or N/O operation	

#### Type tests

Test of the Electromagnetic Compatibility (EMC):

Immunity against electromagnetic Interferences acc. prEN 50082-2:

Impulse voltage and electrical disturbance test acc. to IEC 60255:

Impulse voltage test acc. to IEC 60255-5 class III Electrical disturbance test acc. to IEC 60255-5 class III Emissions acc. to EN 50081-2: Emissions acc. to EN 55011/CISPR11 class B1)

Mechanical tests: Shock resistance acc. to IEC 6068-2-27 15 q/11 ms Bumping acc. to IEC 6068-2-29 40 g/6 ms 10 ... 150 Hz/0.15 mm - 2 g Vibration strength acc. to IEC 6068-2-6

### **Environmental conditions**

Ambient temperature, during operation -15°C ...+50°C Storage temperature range -20°C ... +70°C Climatic class acc. to IEC 60721 3K5, except condensation and formation of ice


# General data

Operation class continuous operation Mounting position any position Type of connection terminals with self-lifting clamp-washers Wire cross section sinale wire 2 x (1...1,5 mm<sup>2</sup>) fine braid 2 x (0.75...1,5 mm<sup>2</sup>) DIN rail according to DIN EN 50 022 or screw mounting Protection class acc. to EN 60529

Internal components IP 50 Terminals/with terminal covers IP10/IP 20 Type of casing X200 Flammability class UL94V-0 Weight approx. 650 g

Right to modifications reserved

### Wiring diagram



# Safety instructions

Please check for correct supply voltage!

Electrical equipment shall only be installed by qualified personnel in consideration of the current safety regulations.

Supplementary to this data sheet you will find enclosed "important safety instructions on the proper use of BENDER products."

## Ordering details

Туре	Supply voltage U <sub>H</sub>	Response value	Art.No.
CSD210	AC 220 V	0.1 1 A	B 942 179
CSD211Z	AC 220 V	0.5 5 A	B 942 180
CSD212	AC 220 V AC 230 V DC 110 V AC 24 V DC 24 V	0.1 1 A 2 7 A 1 10 A 1 10 A 1 10 A	B 942 181 B 942 199 B 942 209 B 942 368 B 942 369
CSD230	AC 220 V DC 24 V	0.1 1 A 0.1 1 A	B 942 182 B 942 213
CSD231	AC 220 V	0.5 5 A	B 942 183
CSD232	AC 220 V DC 24 V	1 10 A 1 10 A	B 942 184 B 942 362

Other values on request.

3.6/4.2 F 07.99

<sup>1)</sup> Class B devices are suitable for household and industrial use.